

APPLICATION OF NATURAL COMMUTATION TECHNIQUE
TO AN IMPROVED CYCLOCONVERTER TYPE HIGH-FREQUENCY LINK
INVERTER WITH CENTER-TAPPED TRANSFORMER

NGE CHEE LIM

A thesis submitted in fulfilment of the
requirements for the award of the degree of
Master of Engineering (Electrical)

Faculty of Electrical Engineering
Universiti Teknologi Malaysia

DECEMBER 2005

ABSTRACT

This thesis presents a new isolated cycloconverter type high frequency (HF) link dc to ac power converter (inverter) that consists of three arms of bidirectional switches at transformer secondary. This topology has the advantage of light weight and reduced switch count, compared to other types of HF link inverter. However, like all HF link inverter topologies, this topology also suffer high voltage surge problem and power device switching loss. In order to overcome these problems, two sets of switching technique, namely the asymmetric bipolar PWM control and edge-aligned unipolar PWM control, are introduced. These switching techniques utilize natural commutation technique that enables total soft switching operation and voltage surge reduction. Furthermore, the proposed switching techniques are able to reduce the transistor conduction loss due to the existence of freewheeling period. The research work verifies of the proposed topology and switching techniques by means of SPICE simulations. It also describes the natural commutation mechanism for HF link inverter in detail. An open loop laboratory prototype based on the Infineon C167 fixed-point microcontroller was constructed. The results obtained from the experimental rig were found to be in very close agreement with the theoretical prediction and simulation. The laboratory prototype was able to supply output voltage $340V_{\text{rms}}$ as well as $120V_{\text{rms}}$, with THD less than 2.5%. The total power conversion efficiency reaches 86% when the output power was beyond 300W.

ABSTRAK

Tesis ini membentangkan satu penukar kuasa dc ke ac (penyongsang) terpisah transformer frekuensi tinggi jenis *cycloconverter* baru yang mempunyai tiga suis dwi-hala di bahagian sekunder transformer. Topologi ini mempunyai kelebihan ringan dan kurang bilangan suis, berbanding dengan jenis penyongsang terpisah transformer frekuensi tinggi yang lain. Namun demikian, seperti penyongsang terpisah transformer frekuensi tinggi yang lain, topologi ini juga mengalami masalah voltan pusuan dan kehilangan kuasa perkakasan yang tinggi. Untuk mengatasi masalah-masalah ini, dua set teknik pensuisan iaitu *asymmetric bipolar PWM control* dan *edge-aligned unipolar PWM control*, telah diusulkan. Teknik pensuisan ini menggunakan teknik komutasi tabii yang membolehkan operasi pensuisan lembut dan pengurangan voltan pusuan. Tambahan pula, teknik pensuisan yang diusulkan ini adalah berupaya untuk mengurangkan kehilangan konduksi transistor kerana kewujudan tempoh *freewheeling*. Usaha penyelidikan ini penentusahkan topologi dan teknik pensuisan yang diusul dengan melaksanakan simulasi SPICE. Teks ini juga menjelaskan teknik komutasi tabii bagi penyongsang terpisah transformer frekuensi tinggi dengan teliti. Satu prototaip makmal gelung terbuka yang dikawal oleh mikropengawal C167 telah dibinakan. Keputusan yang telah diperolehi daripada eksperimen ini adalah bertepatan dengan jangkauan teori dan simulasi. Prototaip makmal telah mampu membekalkan voltan keluaran $340V_{\text{rms}}$ dan $120V_{\text{rms}}$, dengan THD kurang daripada 2.5%. Efisiensi jumlah penukaran kuasa menjejaki 86% apabila kuasa keluaran melebihi 300W.

TABLE OF CONTENTS

CHAPTER	TITLE	PAGE
	TITLE PAGE	i
	DECLARATION	ii
	DEDICATION	iii
	ACKNOWLEDGEMENT	iv
	ABSTRACT	v
	ABSTRAK	vi
	TABLE OF CONTENTS	vii
	LIST OF TABLES	xi
	LIST OF FIGURES	xii
	LIST OF SYMBOLS AND ABBREVIATIONS	xv
	LIST OF APPENDICES	xvii
1	INTRODUCTION	1
	1.1 Overview	1
	1.2 Objective of Research	3
	1.3 Thesis Structure	4
2	LITERATURE REVIEW	5
	2.1 Introduction	5
	2.2 Single Phase Inverter	6
	2.2.1 Hard-Switching Inverter	6
	2.2.2 Soft-Switching Inverter	8
	2.3 Cycloconverter	10

2.4	High-Frequency Link Inverter	12
2.4.1	HF Link Inverter with Voltage Clamper	14
2.4.2	HF Link Inverter Based on Flyback Converter	14
2.4.2	Natural Commutated Phase Angle Control HF Link Inverter	16
2.5	Summary	18
3	THE PROPOSED HF LINK INVERTER	19
3.1	Introduction	19
3.2	The Proposed Power Circuit	20
3.3	Commutation Mechanism	22
3.3.1	Forced Commutation	23
	3.3.1.1 Forced Commutation at Inverter Stage	23
	3.3.1.2 Forced Commutation at Cycloconverter Stage	26
3.3.2	Natural Commutation	28
3.4	Modified Switching Technique	30
3.4.1	Asymmetric Bipolar PWM Control	31
3.4.2	Edge-Aligned Unipolar PWM Control	34
3.5	Summary	36
4	SIMULATION OF NATURAL COMMUTATION TECHNIQUE	37
4.1	Introduction	37
4.2	Parameters of Simulation Circuits and SPICE Models	39
4.2.1	Simulation Parameters	39
4.2.2	Idealized Magnetic Components	39
4.2.3	Idealized Power Switch Models	41
4.2.4	Idealized Diode Models	42
4.3	Simulation of NCPA Control HF Link Inverter	43
4.4	Simulation of the Proposed HF Link Inverter with ABPWM Control	48

4.5	Simulation of the Proposed HF Link Inverter with EAUPWM Control	55
4.6	Summary	59
5	HARDWARE CONSTRUCTION	60
5.1	Introduction	60
5.2	Gate Control Signal Generation Circuits	61
5.3	Power Circuit	65
	5.3.1 Design of Magnetic Components	66
	5.3.2 Power Devices and Snubber Circuits	70
5.4	Summary	72
6	RESULTS AND ANALYSIS	73
6.1	Introduction	73
6.2	The Overall Performance of the Proposed Topology	73
6.3	Comparison of Simulated and Experimental Operating Waveforms	77
6.4	Experimental Results on the Natural Commutation Technique	81
6.5	Summary	84
7	CONCLUSIONS AND FUTURE WORK	85
7.1	Conclusions	85
7.2	Future Work	86
	LIST OF PUBLICATIONS	88
	REFERENCES	89

APPENDIX A – C

LIST OF TABLE

TABLE NO.	TITLE	PAGE
3.1	Cycloconverter commutation process for different switching condition	31
4.1	Comparison of natural commutation technique for NCPA control HF link inverter and the proposed HF link inverter with ABPWM control	52

LIST OF FIGURE

FIGURE NO.	TITLE	PAGE
2.1	Single-phase inverter (a) half-bridge (b) full-bridge	7
2.2	High-frequency inverter waveforms	7
2.3	Low frequency ac power supply	8
2.4	Single transistor resonant dc-link inverter	9
2.5	Auxiliary resonant commutated pole inverter	10
2.6	Single-phase cycloconverter	11
2.7	HF link cycloconverter with (a) polarity reversing and (b) phase-angle control principle	12
2.8	Dc-dc type HF link inverter	13
2.9	Cycloconverter type HF link inverter	13
2.10	HF link inverter with voltage clamper	14
2.11	Hard-switching Flyback type HF link inverter	15
2.12	Flyback type HF link inverter with regenerative snubber	15
2.13	Natural commutated phase angle control HF link inverter	16
2.14	Asymmetric phase control scheme	17
3.1	Proposed cycloconverter type HF link inverter	20
3.2	Forced commutation at inverter stage	24
3.3	Forced commutation at cycloconverter stage	26
3.4	Natural commutation at cycloconverter stage	28
3.5	ABPWM control signals	32
3.6	Output voltage versus output current plane	33

3.7	EAUPWM control signals	35
4.1	Idealized switches that represent a) transistor at primary stage – SP, and b) bidirectional switch at secondary stage – SS	43
4.2	Simulation circuit of NCPA control HF link inverter	45
4.3	NCPA control topology soft-switching operation at (a) inverter stage (b) cycloconverter stage	46
4.4	Operating waveforms of NCPA control topology, operating in inversion mode	47
4.5	Simulation circuit of the proposed HF link inverter	49
4.6	Soft-switching operation of the proposed topology with ABPWM control at (a) inverter stage (b) cycloconverter stage	50
4.7	Operating waveforms of the proposed topology with ABPWM control, operating in inversion mode	51
4.8	Operating waveforms of the proposed topology with ABPWM control, operating in rectification mode	54
4.9	Soft-switching operation of the proposed topology with EAUPWM control	56
4.10	Operating waveforms of the proposed topology with EAUPWM control, operating in inversion mode	57
4.11	Typical operating waveforms of the proposed topology with EAUPWM control, operating in rectification mode	58
5.1	Photograph of the proposed HF link inverter prototype	61
5.2	Logic circuits for gate control signals	62
5.3	Turn-off delay circuit	62
5.4	MCB167-NET evaluation board	63
5.5	Operation and output waveform in C167 standard PWM generation	64
5.6	Transformer core area and winding area	67
5.7	Typical relationship between magnetic flux density and field strength	70

6.1	Simulation result output voltage and load current waveforms with resistive load (a) 250Ω (b) 30Ω	75
6.2	Experimental result output voltage and load current waveforms with resistive load	75
6.3	Experimental overall efficiency versus output power	76
6.4	Control signals generated from C167 microcontroller and logic circuits	77
6.5	Experimental operating waveforms at phase = 45°	79
6.6	Simulated operating waveforms that are using (a) idealized models and (b) practical models	80
6.7	The first natural commutation at cycloconverter stage	82
6.8	The second natural commutation at cycloconverter stage	83
6.9	Forced commutation at bridge inverter stage	84
7.1	Optimized PWM technique	87

LIST OF SYMBOLS AND ABBREVIATIONS

A_c	-	Winding area
ac	-	Alternating current
A_e	-	Core area
A_e	-	Inductance factor
ABPWM	-	Asymmetric bipolar pulse-width modulation
B	-	Flux density
B_{peak}	-	Peak flux density
B_{sat}	-	Saturation flux density
C_f	-	Filter capacitor
C_{out}	-	Transistor output capacitance
C_s	-	Snubber capacitor
CPLD	-	Complex programmable logic device
CPU	-	Center processing unit
dc	-	Direct current
DSTP	-	Destination pointer
EAUPWM	-	Edge-aligned unipolar pulse-width modulation
f	-	Output frequency
f_{CPU}	-	CPU clock frequency
H	-	Flux intensity
H_{peak}	-	Peak flux intensity
HF	-	High frequency
i_{out}	-	Output current
l_g	-	Magnetic core gap length
L	-	Inductance
LC	-	Inductor-capacitor combination
L_f	-	Filter inductor
N	-	Number of transformer/inductor turn
IGBT	-	Insulated gate bipolar transistor
m_f	-	Modulation ratio

M_I	-	Modulation index
$M1 - M4$	-	Transistors at transformer primary of the proposed topology
MX, MY, MZ	-	Transistors at transformer secondary of the proposed topology
SX, SY, SZ	-	Bidirectional switches of the proposed topology
MOSFET	-	Metal oxide silicon field effect transistor
N	-	Number of turn
NCPA	-	Natural commutation phase angle
RC	-	Resistor-capacitor combination
RCD	-	Resistor-capacitor-diode combination
R_s	-	Snubber resistor
SRCP	-	Source pointer
PWM	-	Pulse-width modulation
SPICE	-	Simulation program with integrated circuit emphasis
SPWM	-	Sinusoidal pulse-width modulation
THD	-	Total harmonic distortion
PEC	-	Peripheral event controller
PPx	-	Period register
PTx	-	Timer register
PWMCONx	-	Common register of PWM module
PWx	-	Pulse-width register
t_d	-	Dead time
t_{ov}	-	Overlapped turn-on time
v_{out}	-	Output voltage
V_{rms}	-	Root-mean-square voltage
V_s	-	Voltage source
ZCS	-	Zero current switching
ZVS	-	Zero voltage switching
ΔB	-	Total flux density swing
μ_ε	-	Effective permeability

LIST OF APPENDICES

APPENDIX	TITLE	PAGE
A	Schematic of IGBT Gate Driver Circuit	93
B	Keil μ Vision2 IDE Source Code Listings	95
C	SPICE Simulation Netlist	97

CHAPTER 1

INTRODUCTION

1.1 Overview

Prolonged global energy crisis has led to extensive research interest in renewable energy sources. As fossil and nuclear fuels are gradually depleting, wind and solar power can be explored to meet the growing electricity demand [1]. Such systems normally need dc to ac power converters or commonly known inverters as interfaces between the loads and the energy sources. The inverter generally serves two purposes: to convert dc voltage source to commercial ac voltage, and to provide electrical isolation. With bidirectional power flow ability, the inverter is able to allow the ac power produced to supply stand-alone electrical loads or to feed the grid.

Pulse-width modulated voltage source inverter with an output filter and a 50Hz isolation transformer is the conventional topology used to meet the abovementioned requirements. The inverter uses pulse width modulation (PWM) scheme to synthesize output voltage close to a sine wave, which is then filtered by using low pass filter. The isolation transformer electrically isolates the load from the source; hence preventing the output returns dc-common with the input returns. With the advancement of power semiconductor technology, the power switches can be operated at high frequency, thus reducing the size of filter. Nevertheless, the transformer size remains large so long as the transformer current is not alternating in high frequency. As a result, high-frequency (HF) link inverter configurations, which

utilize HF transformer, have become an important alternative to the conventional 50Hz inverter [2].

There are two popular HF link inverter topologies, namely the “dc/dc converter” type and the “cycloconverter” type [3]. Dc/dc converter type HF link inverter is simple and robust, and is now commercially available. The dc link at the transformer secondary provides stability to the system but prevents bidirectional power flow. Another drawback of this inverter is that it consists of at least three power conversion stages. Cycloconverter type HF link inverter topologies are presently gaining more research interest. The topology allows bidirectional power flow, and is able to compensate harmonics and reactive powers. It normally consists of only two power conversion stages; hence reduce power device conduction loss.

However, both types of HF link inverter suffer from the problem of voltage surge at the transformer secondary because of fast alternating transformer current. Dissipative snubber proved to be effective to solve this problem but it reduces total efficiency. Active clamp circuits, which provide higher efficiency are also feasible but will lead to sophisticated circuit configuration and control method [4-5].

Another problem faced by HF link inverter is high transistor switching loss. Yonemori et al proposed the so-called “soft-switching phase-shifted PWM high-frequency inverter-linked cycloconverter”, which incorporates voltage-clamped quasi-resonant technique [6] to overcome this problem. It consists of a single-phase auxiliary resonant commutated pole inverter, and a bridge type cycloconverter. Chandhaket et al proposed a new HF link inverter that consists of energy regenerating snubber assisted SPWM inverter and the flyback type cycloconverter [7]. This technique is able to simultaneously provide soft-switching operation as well as voltage surge reduction. Matsui et al developed a more promising cycloconverter type HF link inverter topology that employs natural commutation technique to solve both problems without requiring additional circuit [8-10]. Asymmetric control is applicable to this topology, which further improves the total efficiency by reducing transistor conduction loss. The main drawback of this configuration is that, it requires four bidirectional switches at the transformer secondary.

1.2 Objective of Research

From the literature review conducted, it appears that natural commutated phase angle (NCPA) control HF link inverter proposed by Matsui is one of the most potential cycloconverter type HF link inverter topologies. The natural commutation technique employed is the key in solving the voltage surge and switching loss problems without additional circuitry. However, as already been mentioned, the number of power switches is high. This project is aimed at improving the topology by means of the following objectives:

- To propose a cycloconverter type HF link inverter that consists of only three bidirectional switches at transformer secondary. This would therefore result in reduced number of power devices, gate driver circuits and the associated supplementary circuits. It is also expected that the conduction loss would decrease.
- To describe the details of natural commutation technique, due to the absence of literature that describes natural commutation mechanism for HF link inverter. A summary of cycloconverter commutation process for different switching condition is provided to aid the design of modified overlapped switching technique.
- To introduce two sets of overlapped switching technique, namely the asymmetric bipolar PWM control and edge-aligned unipolar PWM control that adapt natural commutation technique. Simulation is performed to verify and analyze the proposed switching techniques.
- To develop a laboratory prototype in order to show the viability of the proposed topology and its switching techniques.

1.3 Thesis Structure

The work undertaken in meeting the above objectives is most logically divided into seven chapters. The content of these chapters are outlined as follows:

- Chapter 2 provides an overview to different HF link inverter topologies. Brief discussion on the building blocks of cycloconverter type HF link inverter is also presented to aid further discussion on the proposed topology.
- Chapter 3 presents a new HF link inverter topology with reduced switch counts. The commutation mechanism at primary and secondary stages is described detail. From the analysis on natural commutation technique, two sets of overlapped switching technique are introduced.
- Chapter 4 is dedicated to the SPICE simulation verification of natural commutation technique. Idealized models are used to perform time-domain analysis on the NCPA control and the proposed HF link inverter topologies.
- Chapter 5 explains briefly on how the laboratory prototype of the proposed topology is built. This includes the discussions on the design power circuit and gate signal generation circuits.
- Chapter 6 explains experimental work that completes the verification effort of the proposed ideas. The operating waveforms obtained from SPICE simulations are compared with those of the experimental results.
- Chapter 7 summarizes the work undertaken and highlights the contribution of this thesis. It offers suggestions for future work.

REFERENCES

- [1] B. K. Bose, (2000) "Energy, Environment, and Advances in Power Electronics." IEEE Transaction on Power Electronics, vol.15, issue 4, pp. 688-701.
- [2] L. Xue, et al., (2001) "Topologies of Single-Phase Inverters for Small Distributed Power Generators: An Overview." IEEE Transaction on Power Electronics, vol. 19, issue 5, pp. 1305-1314.
- [3] E. Koutroulis, J. Chatzakis, K. Kalaitzakis and N. C. Voulgaris, (2001) "A Bidirectional, Sinusoidal, High-Frequency Inverter Design." IEE Proceedings – Electric Power Applications, vol. 148, issue 4, pp. 315-321.
- [4] I. Yamato et al., (1990) "High Frequency Link Dc-Ac Converter for UPS with A New Voltage Clamper." IEEE Power Electronics Specialists Conference, pp. 749-756.
- [5] H. Fujimoto, K. Kuroki, T. Kagotani and H. Kidoguchi, (1995) "Photovoltaic Inverter with a Novel Cycloconverter for Interconnection to a Utility Line." IEEE Industry Application Conference, vol. 3, pp. 2461-2467.
- [6] H. Yonemori, A. Chibani and M. Nakaoka, (1991) "New Soft-Switching Phase-Shifted PWM High-Frequency Inverter-Linked Cycloconverter Incorporating Voltage-Clamped Quasi-Resonant Technique." IEEE Power Electronics Specialists Conference, pp. 283-290.

- [7] S. Chandhaket, S. Nagai, M. Nakaoka and Y. Konishi, (2002) “Energy Regenerating Snubber Assisted Sinewave Soft Switching Pulse Modulation Inverter for Renewal and Sustainable Energy Applications.” IEEE International Conference on Communications, Circuits and Systems and West Sino Expositions, vol. 2, pp. 1696-1701.

- [8] M. Matsui, M. Nagai, M. Mochizuki and A. Nabaе, (1996) “High-Frequency Link DC/AC Converter with Suppressed Voltage Clamp Circuits – Naturally Commutated Phase Angle Control with Self Turn-Off Devices.” IEEE Transactions on Industry Applications, vol. 32, issue 2, pp. 293-300.

- [9] M. Matsui, (1996) “Bidirectional Soft Switching Arm Topology for a Nonresonant HF Link Converter.” IEEE Industry Applications Conference, vol. 2, pp.1153-1160.

- [10] M. Matsui and M. Yamagami, (1998) “Asymmetric Control of HF Link Soft Switching Converter for UPS and PV Systems with Bidirectional Power Flow.” IEEE Industrial Applications Conference, vol. 2, pp. 1332-1340.

- [11] N. Mohan, T. Undeland and W. Robbins, (1995) “Power Electronics, Converters, Application and Design. Second Edition.” John Wiley & Sons, Inc.

- [12] D.M. Divan, (1989) “The resonant dc link converter – A new concept in static power conversion.” IEEE Transactions on Industry Applications, vol. 25, pp. 317–325.

- [13] R. W. De Donker and J. P. Lyons, (1990) “The Auxiliary Resonant Commutated Pole Converter.” IEEE Industrial Applications Conference, vol. 2, pp. 1228-1235.

- [14] M. McMurray, (1972) “The Theory and Design of Cycloconverters.” The MIT Press.

- [15] R. Yamada, K. Kuroki, J. Shinohara and T. Kagotani, (1993) "High-Frequency Isolation UPS with Novel SMR." International Conference on Industrial Electronics, Control, and Instrumentation, vol. 2, pp. 1258-1263.
- [16] M. Huang, J. Ying, D. Xu, and W. Lin, (1999) "Full-Bridge Current Mode High-Frequency Link Inverters." IEEE International Conference on Power Electronics and Drive Systems, vol. 2, pp. 961-965.
- [17] M. H. Rashid, (1993) "SPICE for Power Electronics and Electric Power." Prentice Hall.
- [18] J. Salmon, E. Bocamcea, R. Bhargava and E. Nowicki, (1996) "SPICE3 Simulation Technique in Power Electronics." IEEE Canadian Conference on Electrical and Computer Engineering, vol. 2, pp. 651-654.
- [19] O. Apeldoorn, S. Schroder and R. W. De Doncker, (1997) "A New Method for Power Electronics System-Simulation with PSpice." International Symposium on Industrial Electronics, vol. 2, pp. 217-222.
- [20] M. Z. Ramli, (2004) "Rekabentuk Penyongsang Frekuensi Tinggi Dwi-Arah untuk Aplikasi Tersambung ke Grid." Universiti Teknologi Malaysia: Thesis M.E.E.
- [21] Keil Elektronik GmbH and Keil Software, (2000) "MCB167-NET Board, High-Speed Microcontroller Board for Infineon 167 and ST10-167/168 Variants with Dual CAN and Ethernet Controller." User's guide.
- [22] Infineon Technologies AG., (2000) "C167CS Derivatives, 16-Bit Single-Chip Microcontroller." User's manual.
- [23] S. R. Bowes, (1975) "New Sinusoidal Pulse-Width Modulated Inverter." Proceedings of IEE, vol. 122, issue 11, pp. 101-105.

- [24] S. R. Bowes, (1998) "Modulation Strategy for Single Phase PWM Inverter." Electronics Letters, vol. 34, pp. 420-422.
- [25] A. I. Pressman, (1977) "Switching and Linear Power Supply, Power Converter Design." Hayden Book Company, Inc.
- [26] Ferroxcube Corporation, (2002) "Soft Ferrites and Accessories." Data handbook.
- [27] K. H. Billings, (1989) "Switchmode Power Supply Handbook." McGraw-Hill, Inc.
- [28] R. C. Dodson, P. D. Evans, H. Tabatabaei Yazdi and S. C. Harley, (1990) "Compensating for Dead Time Degradation of PWM Inverter Waveforms." Proceedings of IEE, vol. 137, issue 2, pp. 73-81.
- [29] P. T. Krein, R. S. Balog and Xin Geng, (2002) "High-Frequency Link Inverter for Fuel Cells Based on Multiple-Carrier PWM." IEEE Transactions on Power Electronics, vol. 19, issue 5, pp. 1279-1288.

Soft switching techniques such as zero-voltage-switching (ZVS) or zero-current-switching (ZCS) must be used to alleviate the highest loss bar in Fig. 1.4. The secondary side body diode losses can be saved using two methods. Hardware results are shown for both discrete transformer and integrated transformer prototypes. Chapter 4 summarizes the conclusions and proposes ideas for future work in an extension of the integrated transformer concept beyond just integrating the two gate drive transformers with the main power transformer. The two output inductors are further integrated with the three winding transformer. The topology selection for a compact high frequency, high current and low voltage converter is driven by thermal performance and power density. Four methodologies adopting the constant switching frequency, variable switching frequency, constant pulse width modulation and variable pulse width modulation concepts are proposed in this paper. MATLAB/Simulink has been chosen to implement these techniques due its fast prototyping, simple hardware and software design. The simulation and experimental results are presented. Keywords: Solid state transformers, Single Phase Matrix Converter (SPMC), PWM technique, MATLAB/Simulink.

1. Introduction. bi-directional switches coupled with high frequency ac The application of safe commutation strategy as proposed by transformer that operate synchronously. High frequency Z. Idris [7] is represented by Fig.6 to Fig. The cycloconverter on the transformer secondary converts the high frequency square wave into a low frequency sinusoidal PWM waveform. From our literature review, the most promising solution employs natural commutation technique [7]. The problem of voltage surge is reduced without additional circuitry. Figure 4: Proposed cycloconverter type HF link inverter 50 Journal - The Institution of Engineers, Malaysia (Vol. 67, No. 1, March 2006) 049-056 cycloconverter 6/22/06 12:01 PM Page 51 CYCLOCONVERTER-TYPE HIGH FREQUENCY LINK INVERTER FOR PHOTOVOLTAIC APPLICATION through these diodes. At t_3 , transistors M3 and M4 turn on at zero voltage switching (ZVS) condition. Natural Commutation occurs only in AC circuits, and it is named so because it doesn't require any external circuit. When a positive cycle reaches to zero and the anode current is zero, immediately a reverse voltage (negative cycle) is applied across the Thyristor which causes the Thyristor to turn OFF. A Natural Commutation occurs in AC Voltage Controllers, Cycloconverters, and Phase Controlled Rectifiers. Forced Commutation. As we know there is no natural zero current in DC Circuits like as natural commutation. So, Forced Commutation is used in DC circuits and it is also called as DC commutat... Application of Natural Commutation Technique to Center-Tapped HF Link Inverter. Conference Paper. Feb 2006. Output waveform control is improved because the dead time in the cycloconverter PWM can be eliminated. The main circuit configuration, the PWM method of the cycloconverter used to obtain a sinusoidal output voltage and the switching method of the inverter are described. The experimental results of a 1 kVA DC/AC converter using a high-frequency link of 20 kHz in both single-phase and three-phase output are discussed. An improved Mapham's inverter for high-frequency space power conversion is presented. The proposed inverter system uses a starting commutator to facilitate the starting of the conventional inverter under full-load conditions.